

Skype



---

## PINLITE

---

PinLite Micro Solar Station has been designed to cover the first needs of primary consumptions.



Bornay PinLite

### Why PinLite Micro Solar Station?

---

The PinLite Micro Solar Station has been designed to cover the first needs of primary consumptions.

Many times or places there is a mobile phone and there is not electricity, including some times lighting elements.

With the PinLite Micro Solar Station, is given access to these basic services in a easy way, simple and economic. the PinLite Micro Solar Station with small dimensions, is composed of: the micro station, one 20 Wp solar panel, two 3 W led light bulbs and a USB set of connections.

---

What is included into the PinLite Micro Solar Station?

---

- One Micro Station.
- One 20 Wp solar module.
- Two 3 W led bulbs.
- One USB / RJ10 set of connectors.

The PinLite Micro solar station has inside a Li-Ion battery capable of storing energy and supply it to the consumption of the system.

The PinLite Micro solar station has one USB connector where to recharge a mobile phone, as well as two connectors RJ10 type where led bulbs are connected.

Light bulbs have integrated a RJ10 connector for turns on/off.

## SPECIFICATIONS

### PinLite Micro Solar specifications

#### Input

Solar module	20 Wp. max
Voltage	14 – 22 Vcc
Connectors	+ / - MC3 type

#### USB Output

Voltage	5 Vcc
Current	Máx. 1 Amp

#### RJ10 Output (x2)

Voltage	12 Vcc
Current	0,5 Amp. max

#### Battery

Type	Li-Ion
Voltage	12 Vcc
Capacity	9 Amp
Dimensions	210 x 210 x 45 mm.
Weight	850 grs.
Autonomy	2 bulbs + mobile = 4 hours 1 bulb + mobile = 8 hours

### Solar module specifications

Power	Pmax	20 Wp ± 3%
Efficiency		15 %
Nominal voltage	Vmpp	18 Vcc
Open circuit voltage	Voc	21,2 Vcc
Nominal current	Impp	1,11 A
Short circuit current	Isc	1,16 A

#### Mechanical

Cell type	Monocrystalline	2 x 18
Dimensions		350 x 495 x 25 mm
Weight		2,2 Kgr.

Glass	Tempered 3,2 mm
Frame	Anodic
<b>Bulb specifications</b>	
Power	3 W
Voltage	12 Vcc
Leds	3 x Edison 45 x 45 mm.
Bulb cap	Aluminium with interruptor
Wire	4 mts.
Connector	RJ 10

## DOWNLOADS


---

### BORNAY PINLITE ENG

 [Bornay-PinLite-eng.pdf](#) ( 4.1 MiB )  
Size: 4.1 MiB

---

### CATÁLOGO GENERAL 2020

 [Catalogo-Bornay-0520.pdf](#) ( 21.51 MiB )  
Size: 21.51 MiB

---